

Source File: lab19.asm
Input: Standard Input
Output: Standard Output
Value: 2

Write a program to reverse the elements of an integer array in place. Do not copy the elements to any other array. Use the following initialized variables:

```
1 SECTION .data
2 myArray times 40 dd 0
3 length equ ($ - myArray) / 4
```

Begin by using the `loop` instruction with indirect or indexed addressing to initialize the elements of the integer array from standard input. Use a second `loop` instruction with indirect or indexed addressing to reverse the elements of the integer array in place.

Use the following code segment as a guide to display the hexadecimal contents of an area of memory. Use this code segment to display the contents of the array three times—before the array is initialized, after the elements of the array have been initialized, and after the elements of the array have been reversed.

```
1 mov esi, myArray ; esi = starting offset
2 mov ecx, length ; ecx = # of units
3 mov ebx, 4 ; ebx = unit size (1=byte, 2=word, 4=dword)
4 call DumpMem
```

(The `DumpMem` procedure is explained in Section 5.4.)

Add an identification section as shown below to the top of your source file.

```
; Your name
; CS 3304
; Lab 19
```

A sample execution sequence is shown in Figure 1. To use the `Makefile` as distributed in class, add a target of `lab19` to `targetsAsmLanguage`.

```
1 newuser@csunix ~/3304/19> cp /usr/local/3304/data/19/* .
2 newuser@csunix ~/3304/19> make lab19
3 nasm -f elf32 -l lab19.lst -o lab19.o lab19.asm -I/usr/local/3304/include/ -I.
4 ld -m elf_i386 --dynamic-linker /lib/ld-linux.so.2 -o lab19 lab19.o \
5 /usr/local/3304/src/Along32.o -lc
6 newuser@csunix ~/3304/19> ./irvine_test.sh lab19 01.dat
7
8 Dump of offset 0804A010
9 -----
10 00000000 00000000 00000000 00000000 00000000 00000000 00000000 00000000
11 00000000 00000000 00000000 00000000 00000000 00000000 00000000 00000000
12 00000000 00000000 00000000 00000000 00000000 00000000 00000000 00000000
13 00000000 00000000 00000000 00000000 00000000 00000000 00000000 00000000
14 00000000 00000000 00000000 00000000 00000000 00000000 00000000 00000000
15
16 Dump of offset 0804A010
17 -----
18 FFFFFFFF FFFFFFFF FFFFFFFC FFFFFFF8 FFFFFFF0 FFFFFFE0 FFFFFFFC0 FFFFFF80
19 FFFFFF00 FFFFFFE00 FFFFFFC00 FFFFF800 FFFF000 FFFF000 FFFFC000 FFFF8000
20 FFFF0000 FFFE0000 80000001 80000000 00000000 00000001 00000002 00000004
21 00000008 00000010 00000020 00000040 00000080 00000100 00000200 00000400
22 00000800 00001000 00002000 00004000 00008000 00010000 00020000 7FFFFFFF
23
24 Dump of offset 0804A010
25 -----
26 7FFFFFFF 00020000 00010000 00008000 00004000 00002000 00001000 00000800
27 00000400 00000200 00000100 00000080 00000040 00000020 00000010 00000008
28 00000004 00000002 00000001 00000000 80000000 80000001 FFFE0000 FFFF0000
29 FFFF8000 FFFF0000 FFFF0000 FFFF0000 FFFF8000 FFFF0000 FFFF0000 FFFF0000
30 FFFFFF80 FFFFFFC0 FFFFFFE0 FFFFFF00 FFFFFF80 FFFFFFC0 FFFFFFE0 FFFFFF80
31 newuser@csunix ~/3304/19>
```

Figure 1. Commands to Assemble, Link, & Run Lab 19